

Mobile V6N Quick Start Guide

1. Connect monitor input into video 1 or VGA out on the DB25 connector
(If you are connecting with a VGA monitor you must hit the VGA button on the remote once the unit is fully booted)
2. Connect camera inputs into the DB37 connector.

Entering Setup:

Username: 00000

Password: 88888888

Setting up Motion Based Recording:

1. Hit setup key on remote
2. Navigate to Setup>Event Setup>MD
3. Select switch to yes for the cameras you desire to have motion detection on
4. Hit enter on setup to change the motion detection area that you desire, or hit setup on the remote to cover the whole area.
5. Select Alarm and lock to yes for the cameras you desire to have motion on.
6. Hit apply
7. Exit setup and reboot the DVR.

Setting up Continuous record on all cameras

1. Navigate to Setup>Schedule
2. Set schedule to ON
3. For Date use the enter key till it says every
4. For times it should say 00:00 – 23:59
5. Hit apply
6. Reboot DVR

Setting up the Network

1. Navigate to setup>Network
2. Enter IP address
3. Enter Subnet Mask
4. Enter Gateway
5. Hit Apply
6. Reboot DVR